



Smart Light Bulb
User Manual


NEW CUSTOMER INSTALLATION

If you've received this light bulb as part of your initial order with a Frontpoint Hub, we've done the set-up process for you!


- 1 Screw the light bulb into a light fixture and turn it on.
- 2 Control the light using our Frontpoint app and rename the light by going online to [MyFrontpoint.com](https://myfrontpoint.com) >Settings >Devices (optional).

EXISTING CUSTOMER INSTALLATION

Based on your system's panel, please follow the corresponding instructions below:



Frontpoint
Simon XT



Frontpoint
IQ Panel



Frontpoint Hub

*If you've received this light bulb as an additional order and currently have a **Frontpoint Simon XT** or **IQ Panel** in your home, please call 877-602-5276 for step by step instructions.*

If you've received this light bulb as an additional order and have a **Frontpoint Hub** in your home:

- 1 Screw the light bulb into the desired light fixture; the switch should be OFF.

****Please note:** During the learn-in process, the light bulb must be within 30' of the Frontpoint Hub. After the learn-in process, the light bulb can function within 30' of the Frontpoint Hub or another Z-wave device, such as another Z-Wave light bulb. If you need to purchase another light bulb to extend the allowable distance, go online to MyFrontpoint.com >Shop >Home Automation.*

- 2 Hold down the button on the Frontpoint Hub next to the AC adapter for 10-15 seconds until you hear a chirp. The Frontpoint Hub's LED light will turn white; this is called "learn-in mode".

- 3 Turn the light fixture ON. The light bulb will then flash two times to indicate a successful connection.
- 4 Press the button on the Frontpoint Hub again to exit learn-in mode. The LED light will change from white to green.
- 5 The light bulb will appear listed in your app within 3 to 5 minutes, giving you the ability to turn on/off and dim your light. If you wish to rename the light, you can do so by going on-line to MyFrontpoint.com >Settings >Devices.

USAGE INSTRUCTIONS:

Use the Frontpoint app to control the light, or login to my.frontpointsecurity.com to control through your web browser.

Important: Remember to keep the light switch in a permanent ON position to be able to use with the app.

To MANUALLY turn on your light without using the app: Flip the switch OFF and then ON again. If you need to turn the light bulb off without using the app: turn the light OFF, ON, OFF, ON, and the light will turn off after a few seconds.

To return your bulb to factory defaults: Cycle the switch on the light fixture OFF/ON four times (8 switches total) within 4 seconds. The light bulb will flash 2 times to indicate a successful reset. This can be used when switching the light bulb from one control panel and adding it to another.

To AUTOMATE your light bulb:

Login to your account at my.frontpointsecurity.com and click "Automation", found on the left-side panel. Within this section, you can add rules, schedules, or scenes to make your life easier.

- Rules are event-triggered responses of the light based on your indicated preferences. For example, turn on a light when sensor activity has been detected.
- A schedule can be set so your light bulbs turn on/off or dim based on the times you select.
- A scene can be set to control multiple devices with one click. For example, set a scene of "sleep" to arm your system and turn off all lights at the same time.

TROUBLESHOOTING:

If the bulb can't be added into your ecosystem:

- 1 Bring the light bulb closer to the control panel and try again.
- 2 If your control panel is a hub, please make sure hub is plugged in and try again.
- 3 Return your bulb to factory defaults (directions on page 6). After a successful reset, try adding the bulb again.

If the light isn't responding to remote commands:

- 1 If the light bulb was just added in, please wait a few minutes and try again. It is possible that the light bulb needs additional time before it can communicate with the control panel and respond properly with remote commands.

- 2 Please move the control panel and the bulb closer together and try again. If this is successful, consider keeping the light and control panel closer together, or purchasing additional bulbs as range extenders.



Need more help?

Call us at 877-602-5276.

SAFER. SMARTER. SIMPLER.

www.frontpoint.com